

SEALEY

1.4/2.8KW CERAMIC HEATER WITH TELESCOPIC TRIPOD STAND 230V

MODEL NO: CH2800S

Thank you for purchasing a Sealey product. Manufactured to a high standard, this product will, if used according to these instructions, and properly maintained, give you years of trouble free performance.

IMPORTANT: PLEASE READ THESE INSTRUCTIONS CAREFULLY. NOTE THE SAFE OPERATIONAL REQUIREMENTS, WARNINGS & CAUTIONS. USE THE PRODUCT CORRECTLY AND WITH CARE FOR THE PURPOSE FOR WHICH IT IS INTENDED. FAILURE TO DO SO MAY CAUSE DAMAGE AND/OR PERSONAL INJURY AND WILL INVALIDATE THE WARRANTY. KEEP THESE INSTRUCTIONS SAFE FOR FUTURE USE.



Refer to instruction manual



Warning! Hot surface



DO NOT cover



Indoor use only

1. SAFETY

This product is not suitable for primary heating purposes. This product is only suitable for well insulated spaces or occasional use.

1.1. ELECTRICAL SAFETY

- **WARNING!** It is the user's responsibility to check the following:
Check all electrical equipment and appliances to ensure that they are safe before using. Inspect power supply leads, plugs and all electrical connections for wear and damage. Sealey recommend that an RCD (Residual Current Device) is used with all electrical products. You may obtain an RCD by contacting your local Sealey stockist.

If the product is used in the course of business duties, it must be maintained in a safe condition and routinely PAT (Portable Appliance Test) tested.

Electrical safety information, it is important that the following information is read and understood.

Ensure that the insulation on all cables and on the appliance is safe before connecting it to the power supply.

Regularly inspect power supply cables and plugs for wear or damage and check all connections to ensure that they are secure.

Important: Ensure that the voltage rating on the appliance suits the power supply to be used and that the plug is fitted with the correct fuse - see fuse rating in these instructions.

- * **DO NOT** pull or carry the appliance by the power cable.
- * **DO NOT** pull the plug from the socket by the cable.
- * **DO NOT** use worn or damaged cables, plugs or connectors. Ensure that any faulty item is repaired or is replaced immediately by a qualified electrician.

This product is fitted with a BS1363/A 13 Amp 3 pin plug.

If the cable or plug is damaged during use, switch off the electricity supply and remove from use.

Ensure that repairs are carried out by a qualified electrician.

Replace a damaged plug with a BS1363/A 13 Amp 3 pin plug. If in doubt contact a qualified electrician.

a) Connect the GREEN/YELLOW earth wire to the earth terminal 'E'.

b) Connect the BROWN live wire to the live terminal 'L'.


c) Connect the BLUE neutral wire to the neutral terminal 'N'.

Ensure that the cable outer sheath extends inside the cable restraint and that the restraint is tight.

Sealey recommend that repairs are carried out by a qualified electrician.

1.2. GENERAL SAFETY

- ✓ Familiarise yourself with the applications and limitations of the heater.
- ✓ Ensure that heater body is positioned on a firm, horizontal dry surface.
- ✓ Keep away from flammable objects/materials/surfaces. This product gets very hot during use. Use in a location where accidental contact (particularly by children) is unlikely.
- ✓ Ensure on/off switches are set to 'off' before connecting power cord to power supply.
- ✓ Ensure the heater is in good order and condition before use. If in any doubt do not use the unit and contact an electrician.
- ✓ Only use recommended attachments and parts. To use unauthorised parts may be dangerous and will invalidate your warranty.
- ✓ Check that element guard is in place, undamaged and firmly attached.
- ✓ Keep tools and other items away from the heater when it is in use.
- ✓ Keep the work area clean and clear of unnecessary items.
- ✓ Keep children and unauthorised persons away from the heater, as it gets **very hot**. Children of less than 3 years should be kept away unless continuously supervised.
- ✓ Disconnect from mains and allow to cool before moving or attempting any cleaning or maintenance.
- * **DO NOT** get the heater wet or use in damp or wet locations or areas where there is condensation.
- * **DO NOT** locate the heater below the power outlet.
- * **DO NOT** remove plug from mains supply by pulling on power cord.
- * **DO NOT** move the heater whilst in operation or even when still warm.
- * **DO NOT** touch the heater elements, even when cold.
- ✓ **Always** switch off heater, disconnect from power supply and allow cooling for at least **one** hour before attempting to touch heater cassette.
- * **DO NOT** remove safety guard whilst heater is switched on. Turn off and allow cooling (as above) before servicing.
- * **DO NOT** disassemble the heater for any reason. The heater must be checked by qualified personnel only.
- * **DO NOT** use this product to perform a task for which it has not been designed.



- × **DO NOT** operate heater without safety guard or elements installed.
- ☐ **WARNING! If a fuse blows, ensure it is replaced with an identical fuse type and rating.**
- ☐ **WARNING! If supply trips at consumer unit, ensure correct rating of supply and appliance. If further tripping occurs consult a qualified electrician.**
- × **DO NOT** place any object on the safety guard of the heater cassette at any time.
- ☐ **WARNING! Ensure the heater is at least 2m from any object.**
- × **DO NOT** leave unattended.

This heater is not equipped with a device to control the room temperature. **DO NOT** use this heater in small rooms when they are occupied by persons not capable of leaving the room on their own, unless constant supervision is provided.

- ✓ When not in use, store the heater carefully in a safe, dry, childproof location.

NOTE: This appliance can be used by children aged from 8 years and above and persons with reduced physical, sensory or mental capabilities or lack of experience and knowledge if they have been given supervision or instruction concerning use of the appliance in a safe way and understand the hazards involved. Children shall not play with the appliance. Cleaning and user maintenance shall not be made by children without supervision.


NOTE: Children aged from 3 years and less than 8 years shall only switch on/off the appliance provided that it has been placed or installed in its intended normal operating position and they have been given supervision or instruction concerning use of the appliance in a safe way and understand the hazards involved. Children aged from 3 years and less than 8 years shall not plug in, regulate and clean the appliance or perform user maintenance.

2. INTRODUCTION

Tripod mounted, powder coated metal construction. Two ceramic heating elements provide instant heat when required. Polished reflectors maximize heat emission. Output controlled by rocker switches fitted to the frame. Supplied with 2m cable fitted with 3-pin plug. Foldable legs for easy storage.

3. SPECIFICATION


Model no	CH2800S
Max. height	1760mm
Min. height	1500mm
Power.....	1400/2800W
Supply.....	230V - 13A



HEATER VIEWED FROM REAR

*Heater and stand Identification fig.1

- | | |
|---------------------------|-----------------------------------|
| 1) *Heater Element | 7) Tripod |
| 2) *Safety Guard | 8) Spring loaded plunger |
| 3) *Heater Body | 9) Heater swivel mounting bracket |
| 4) Handle and thumb screw | 10) Adaptor and thumb screw |
| 5) *Power on Neon | 11) Hex screw and stiff nut |
| 6) *Power On/Off | 12) Rubber sleeve |



4. ASSEMBLY

- 4.1. Remove contents from packaging and check against list. In the unlikely event of missing or damaged parts contact your Sealey stockist immediately.
- 4.2. Fit adaptor [item 10] to heater swivel bracket [item 9] with M8 hexagon head screw and hexagon stiff nut [item 11] in (fig.2). Torque screw to obtain grip without clamping the heater bracket totally. The heater angle can be adjusted about this fixing between constraints.
- 4.3. The tripod will be supplied assembled. Retract plunger [item 8] in (fig.1) and pull or push central column tube through sleeve until the plunger "clicks" into the next location hole. This will be the stands maximum height setting.
- 4.4. Slide the handle [item 4] down the central column and fix with the thumb screw through the M8 hole.
- 4.5. Fit the rubber sleeve [item 12] into the top of the central column in (fig.2).
- 4.6. Slide adaptor c/w heater into central column full depth and clamp with thumb screw.

5. OPERATION

- ❑ **WARNING! Ensure you read, understand and apply the safety instructions in Section 1 before using the heater.**

NOTE! The ceramic element is fragile and therefore it is important that it is not subjected to any unnecessary shocks or vibration and is not moved when it is on or until cooled down.

- 5.1. Ensure the heater is at least 2m from any object.
- 5.2. Plug in the heater and switch it on. Each element has its own switch, see fig.3.
- 5.3. When the heater is no longer required, switch off and unplug the unit.
IMPORTANT: DURING RELOCATION, THE HEATER SHOULD REMAIN SWITCHED OFF AND DISCONNECTED FROM THE POWER SUPPLY.
- 5.4. In the event of the heater being knocked over, a safety cut-out switch, which activates at an angle of $35^{\circ} \pm 10^{\circ}$, will disable the heater.
- 5.4.1. Follow these steps to re-start the heater.
 - a) Switch 'off' the heater at the on/off switches, see fig.3.
 - b) Disconnect the power cord from the power supply.
 - c) Return the heater to a standing position.
 - d) If no damage has occurred to elements, replace safety guard if applicable, re-connect power cord to the power supply and switch the heater back on.
- 5.4.2. Should the power cord require replacement, a complete wiring loom should be purchased and fitted by a suitably qualified person.

6. MAINTENANCE

- ❑ **WARNING!** Disconnect from the mains and allow to cool before moving or attempting any cleaning or maintenance.

- 6.1. Clean the heater and guard with a damp cloth and some mild detergent.
- 6.2. To replace any of the elements, contact your authorised Sealey stockists.
- 6.3. Use a vacuum cleaner outside the grille guard to clean dust from heater elements.
 - × **DO NOT** use abrasive cleaners or polishes on casing or guard.
 - × **DO NOT** touch the elements unless essential to do so.
- 6.4. When not in use, store the heater carefully in a safe, dry, childproof location.



WEEE REGULATIONS

Dispose of this product at the end of its working life in compliance with the EU Directive on Waste Electrical and Electronic Equipment (WEEE). When the product is no longer required, it must be disposed of in an environmentally protective way. Contact your local solid waste authority for recycling information.



ENVIRONMENT PROTECTION

Recycle unwanted materials instead of disposing of them as waste. All tools, accessories and packaging should be sorted, taken to a recycling centre and disposed of in a manner which is compatible with the environment. When the product becomes completely unserviceable and requires disposal, drain any fluids (if applicable) into approved containers and dispose of the product and fluids according to local regulations.

Note: It is our policy to continually improve products and as such we reserve the right to alter data, specifications and component parts without prior notice. Please note that other versions of this product are available. If you require documentation for alternative versions, please email or call our technical team on technical@sealey.co.uk or 01284 757505.

Important: No liability is accepted for incorrect use of this product.

Warranty: Guarantee is 12 months from purchase date, proof of which is required for any claim.

Sealey Group, Kempson Way, Suffolk Business Park, Bury St Edmunds, Suffolk. IP32 7AR



01284 757500



01284 703534



sales@sealey.co.uk



www.sealey.co.uk